

PRODUCT DATASHEET Strada-SQ-T-DW series





Ordering number C11818
Description C11818_Strada-SQ-T-DW-XP

10.67 mm

Family Strada-SQ **FWHM** 0 degrees Type Lens Efficiency XP-E LED cd/lm Color Transparent Gerber File Available Diameter 25.2 x 25.2 mm

Style Square
Optic Material PMMA
Holder Material Fastening Tape
Status Ready

Height

Ordering number CA11819

Description CA11819_Strada-SQ-T-DW-XP-TAPE

Family Strada-SQ FWHM 0 degrees
Type Lens Efficiency LED XP-E cd/lm Color Transparent Gerber File Available

Diameter 25.2 x 25.2 mm
Height 10.82 mm
Style Square
Optic Material PMMA
Holder Material Fastening Tape
Status Ready

NOTE: The typical divergence will be changed by different color, chip size and chip position tolerance. The typical total divergence is the full angle measured where the luminous intensity is half of the peak value.



PRODUCT DATASHEET Strada-SQ-T-DW series



GENERAL INFORMATION

- Product series especially designed & optimized for XP-E series of LEDs.
- Special care taken to make light distribution as uniform as possible.
- Lens material optical grade PMMA with high UV and temperature resistance (105 degrees of Celcius / 220 degrees of Fahrenheit). Allows use of high current and temperature conditions.

Please find more information about used material from below: http://ledil.fi/sites/default/files/Documents/Technical/Material/PMMA%208N%20UL94_Yellow%20Card.pdf http://ledil.fi/sites/default/files/Documents/Technical/Material/PMMA%208N%20PLEXIGLAS-Datasheet.pdf

- Fastening to heat sink with a PU foam adhesive tape of automotive grade. Please find fastening details by clicking link: http://www.ledil.com/datasheets/DataSheet_TAPE.pdf

NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit boar weaken the strength of the tape.

NOTE 2: Assembly to the surface must be made straight, so the tape bonds constant and balanced with fastening surface. Slanted assembly might cause unbalanced bond to the surface. All surfaces where tape is applied must be clean, dry and free from grease and dirt.

If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer - this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.

